

## 2007 - Exercises II.

1. Decide which of the following codes is linear. Find the standard form of generator matrix for codes that are linear.
  - (a) quaternary code  $C_1 = \{000, 123, 202, 321\}$
  - (b) 6-ary code  $C_2 = \{00, 03, 43, 23, 20, 40\}$
  - (c) ternary code  $C_3 = \{000, 221, 112\}$

2. Compare the set of perfect codes with the set of maximum distance separable codes (*ie.* use  $\subseteq, =, \dots$ ).

3. Let  $C$  be a binary code with generator matrix

$$G = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 1 & 1 \end{bmatrix}.$$

- (a) Write a generator matrix for the code obtained from  $C$  by puncturing the 1st and 4th coordinate.
  - (b) Write a generator matrix for the extended code  $\hat{C}$ .  
(If  $C$  is a linear code over  $\mathbb{F}_q^n$  then  $\hat{C} = \{x_1x_2\dots x_nx_{n+1} \in \mathbb{F}_q^{n+1} | x_1\dots x_n \in C \text{ and } x_1 + \dots x_n + x_{n+1} = 0\}$  is the extended code.)
  - (c) Describe the code that is obtained from a linear code first by extending this code and then puncturing on the new coordinate. What happens if we change the order of these operations?
4. Let  $C$  be a binary linear  $[4, 2]$ -code such that  $C = C^\perp$ . Show that  $C$  contains at least two words of weight 2.
  5. Let  $C$  be a perfect binary linear  $[7, 4]$ -code. Find the value of  $d$ . Suppose that  $C$  is transmitted over a binary symmetric channel with error probability  $p = 0.01$  using the syndrome decoding strategy. Calculate the word error probability.
  6. Consider the linear code  $C$  over the field  $\mathbb{Z}_7$  spanned by the codewords 43352, 24545 and 31433.
    - (a) Find a generator matrix in the standard form for  $C$ .
    - (b) How many different messages can  $C$  encode?
    - (c) Show that a received word containing at most one error can be corrected.